

# WIRE WINDING PW620-15

### **Wire wound precision Potentiometer**

- · High-resolution resistive element with caterpillar winding
- · Short-circuit distances and additional taps available upon request

SYNCHRO DESIGN

· Resistance value and active angle can be customized as desired





## **TECHNICAL DATA**

Housing material	aluminum, anodized
Housing diameter	50.8 mm
Model	synchro size 20
IP code	IP30
Shaft diameter	6 mm
Adjustment speed	max. 360 U/min
Torque	0.05 Ncm
Wiper without limit stops	no
Multiple execution	sixfold
Bearing	ball-bearing
Connection	faston plug / solder-type terminals
Fastening	clamp fixing
Resistance element	caterpillar
Active angle	max. 345°

Resistance values	to 20 kΩ
Resistance tolerance	5%
Linearity tolerance	±0.2 %
Resolution	3434 turns
Capacity	1 W
Temperature range	-30 °C to +80 °C
Temperature coefficient	0.00 17 % / °C
Lifetime typical 10–50 Mio. Cycles The lifetime depends on the application and environmental conditions.	
Vibration*	5-200 Hz, 10 g
Shock*	50 g, 6 ms

#### **Specific features**

2 additional switches, fixed

\*Depending on customer specifications.

Article master number

1577Z01

Optionally available

### **PROTECTIVE HOUSING**

To protect against mechanical damage and extreme environmental conditions, as well as for necessary adaptation gears and additional switches, suitable housings are available in various designs.



For more information on protective housings, click here:www.fsg-sensors.de



## Typical **APPLICATION AREAS**






WIRE WINDING


SYNCHRO DESIGN

# PW620-15

### **DIMENSIONAL DRAWINGS**




### CONNECTION



Standard

- 11 Resistance start
- 12 Wiper
- 13 Resistance end





### **CIRCUIT VARIATIONS**

**Wire-wound** resistive elements with shape on a painted copper wire body in single-turn or multi-turn potentiometers.



- 1 Wiper limited by stops
- 2 Wiper continius rotation without limit stops (over 360°) only for short-up without voltage
- 3 Free arrangement of short-circuit sections
- 4 Free arrangement of taps

## CONTACT

If you have any questions about this or any other FSG product, please do not hesitate to contact us.

# BERLIN (HQ)

- Fernsteuergeräte Kurt Oelsch GmbH Jahnstraße 68 + 70 12347 Berlin
- Info@fsg-sensors.de

   ●
   www.fsg-sensors.de

   ●
   +49 30 6291-1

   ●
   +49 30 6291-277

© Fernsteuergeräte Kurt Oelsch GmbH No guarantee for the correctness, completeness of the contents. The product illustration may ditter from original.